arXiv:1004.3085v1 [cs.IT] 19 Apr 2010

Universal Coding of Ergodic Sources for Multiple Decoders with Side Information

Shigeaki Kuzuoka, Akisato Kimura, and Tomohiko Uyematsu

Abstract

A multiterminal lossy coding problem, which includes various problems such as the Wyner-Ziv problem and the complementary delivery problem as special cases, is considered. It is shown that any point in the achievable rate-distortion region can be attained even if the source statistics are not known.

I. INTRODUCTION

Recently, the authors investigated the following coding problem [1]. Consider a coding system composed of one encoder and J decoders. The encoder observes the sequence generated by a memoryless source with generic variable X. Then, the encoder broadcasts the codeword to the decoders over the noiseless channel with capacity R. The purpose of the j-th decoder is to estimate the value of the target source Z_j as accurately as possible by using the side information Y_j and the codeword sent by the encoder, where $\{Y_j\}_{j=1}^J$ and $\{Z_j\}_{j=1}^J$ may be correlated with X. Accuracy of the estimation of the j-th decoder is evaluated by some distortion measure $d_1^{(j)}$ and it is required that the expected distortion is not greater than the given value Δ_j. Fig. 1 depicts the coding system where $J=3$.

In [1], we proposed a coding scheme which is *universal* in the sense that it attains the optimal rate-distortion tradeoff even if the probability distribution P_X of the source X is unknown, while the side informations $\{Y_j\}_{j=1}^J$ and the targets $\{Z_j\}_{j=1}^J$ are assumed to be generated from X via a known memoryless channel. In [1], we considered only stationary and memoryless sources. In this paper, we extend the result of [1] to the case where sources are stationary and ergodic sources.

As mentioned in [1], our coding problem described above includes various problems as special cases. For example, the Wyner-Ziv problem, i.e. the rate-distortion problem with side information at the decoder [2], is a special case of our problem, where $J=1$ and $Z_1=X$. A variation of the Wyner-Ziv problem, where the side information may fail to reach the decoder [3]–[5], is also included as a special case, where $J=2$, $Y_1=\emptyset$, $Y_2=Y$ and $Z_1=Z_2=X$ (see Fig. 2). Moreover, our coding system can be considered as a generalization

---

S. Kuzuoka is with the Department of Computer and Communication Sciences, Wakayama University, 930 Sakaedani, Wakayama, 640-8510 Japan (e-mail: kuzuoka@ieee.org)

A. Kimura is with NTT Communication Science Laboratories, NTT Corporation, 3-1 Morinosato Wakamiya, Atsugi-shi, Kanagawa, 243-0198 Japan (e-mail: akisato@ieee.org)

T. Uyematsu is with the Department of Communications and Integrated Systems, Tokyo Institute of Technology, 2-12-1 Ookayama, Meguro-ku, Tokyo, 152-8550 Japan (e-mail: uyematsu@ieee.org)

The work of S. Kuzuoka was supported in part by Grant-in-Aid for Young Scientists (B) 22760278. The work of A. Kimura was supported in part by Grant-in-Aid for Young Scientists (B) 20760255.

of the complementary delivery [6], [7]. In fact, a simple complementary delivery problem depicted in Fig. 3 is the case where $J = 2$, $X = \{X_1, X_2\}$, $Y_1 = X_2$, $Y_2 = X_1$, and $Z_j = X_j$ ($j = 1, 2$). Further, our coding problem includes also the problem considered in [8] (depicted in Fig. 4) as a special case, where $J = 2$, $X = \{X_0, X_1, X_2\}$, $Y_j = X_j$ ($j = 1, 2$), and $Z_1 = Z_2 = X_0$.

II. MAIN RESULT

At first, we introduce some notations. We denote by $\mathbb{N}$ the set of positive integers $\{1, 2, \dots\}$. For a set $\mathcal{A}$ and an integer $n \in \mathbb{N}$, $\mathcal{A}^n$ denotes the n-th Cartesian product of $\mathcal{A}$. For a finite set $\mathcal{A}$, $|\mathcal{A}|$ denotes the cardinality of $\mathcal{A}$. Throughout this paper, we will take all $\log$ and $\exp$ to the base 2.

Let $\boldsymbol{X} = X_1 X_2 \dots$ be a stationary and ergodic source with finite alphabet $\mathcal{X}$. For each $n \in \mathbb{N}$, X^n denotes the first n variables $(X_1, X_2, \dots, X_n)$ of $\boldsymbol{X}$ and the distribution of X^n is denoted by P_{X^n}.

Fix $J \in \mathbb{N}$. We consider random variables Y_j (resp. Z_j) taking values in sets $\mathcal{Y}_j$ (resp. $\mathcal{Z}_j$) where j ranges over the index set $\mathcal{J} \triangleq \{1, 2, \dots, J\}$. We assume that, for each $j \in \mathcal{J}$, $\mathcal{Y}_j$ and $\mathcal{Z}_j$ are finite sets. We write

$$\mathcal{Y}_{\mathcal{J}} \triangleq \prod_{j \in \mathcal{J}} \mathcal{Y}_j, \quad Y_{\mathcal{J}} \triangleq \{Y_j\}_{j \in \mathcal{J}}$$

and

$$\mathcal{Z}_{\mathcal{J}} \triangleq \prod_{j \in \mathcal{J}} \mathcal{Z}_j, \quad Z_{\mathcal{J}} \triangleq \{Z_j\}_{j \in \mathcal{J}}.$$

Let $W \colon \mathcal{X} \to \mathcal{Y}_{\mathcal{J}} \times \mathcal{Z}_{\mathcal{J}}$ be a *transition probability*. In the followings, we assume that W is fixed and available as prior knowledge. For each $n \in \mathbb{N}$, let W^n be the n-th extension of W, that is,

$$W^n(y_{\mathcal{J}}^n, z_{\mathcal{J}}^n | x^n) \triangleq \prod_{i=1}^{n} W(y_{\mathcal{J},i}, z_{\mathcal{J},i} | x_i)$$

for any sequences

$$\begin{aligned} x^n &\triangleq (x_1, x_2, \dots, x_n) \in \mathcal{X}^n, \\ y_{\mathcal{J}}^n &\triangleq (y_{\mathcal{J},1}, y_{\mathcal{J},2}, \dots, y_{\mathcal{J},n}) \in \mathcal{Y}_{\mathcal{J}}^n, \text{ and} \\ z_{\mathcal{J}}^n &\triangleq (z_{\mathcal{J},1}, z_{\mathcal{J},2}, \dots, z_{\mathcal{J},n}) \in \mathcal{Z}_{\mathcal{J}}^n. \end{aligned}$$

Then, by a source $\boldsymbol{X}$ and a transition probability W, sources $\boldsymbol{Y}_{\mathcal{J}} \triangleq \{Y_{\mathcal{J},i}\}_{i=1}^{\infty}$ and $\boldsymbol{Z}_{\mathcal{J}} \triangleq \{Z_{\mathcal{J},i}\}_{i=1}^{\infty}$ are induced[1]. In other words, $Y_{\mathcal{J}}^n \triangleq (Y_{\mathcal{J},1}, \dots, Y_{\mathcal{J},n})$ (resp. $Z_{\mathcal{J}}^n \triangleq (Z_{\mathcal{J},1}, \dots, Z_{\mathcal{J},n})$) is a random variable on $\mathcal{Y}_{\mathcal{J}}^n$ (resp. $\mathcal{Z}_{\mathcal{J}}^n$) such that

$$\begin{aligned} & P_{X^n Y_{\mathcal{J}}^n Z_{\mathcal{J}}^n}(x^n, y_{\mathcal{J}}^n, z_{\mathcal{J}}^n) \\ &= P_{X^n}(x^n) W^n(y_{\mathcal{J}}^n, z_{\mathcal{J}}^n | x^n) \\ &= P_{X^n}(x^n) \prod_{i=1}^{n} W(y_{\mathcal{J},i}, z_{\mathcal{J},i} | x_i) \end{aligned}$$

---

[1] Note that the transition probability W is stationary and *memoryless*, while the source $\boldsymbol{X}$ is stationary and ergodic. Further, we assume that W is *known* both to the encoder and decoders, while $\boldsymbol{X}$ is unknown. Universal Wyner-Ziv coding in a setting similar to ours is considered in [9].

for any $x^n \in \mathcal{X}^n$, $y^n_{\mathcal{J}} \in \mathcal{Y}_{\mathcal{J}}$, and $z^n_{\mathcal{J}} \in \mathcal{Z}^n_{\mathcal{J}}$. For each $j \in \mathcal{J}$, $\boldsymbol{Y}_j \triangleq \{Y_{j,i}\}_{i=1}^{\infty}$ (resp. $\boldsymbol{Z}_j \triangleq \{Z_{j,i}\}_{i=1}^{\infty}$) is called the j-th component of $\boldsymbol{Y}_{\mathcal{J}}$ (resp. $\boldsymbol{Z}_{\mathcal{J}}$). Note that the joint distribution $P_{X^n Y^n_j Z^n_j}$ of X^n, $Y^n_j \triangleq (Y_{j,1}, \ldots, Y_{j,n})$, and $Z^n_j \triangleq (Z_{j,1}, \ldots, Z_{j,n})$ is given as a marginal distribution of $P_{X^n Y^n_{\mathcal{J}} Z^n_{\mathcal{J}}}$, that is,

$$\begin{aligned} & P_{X^n Y^n_j Z^n_j}(x^n, y^n_j, z^n_j) \\ & \triangleq \sum_{\hat{j} \neq j} \sum_{y^n_{\hat{j}}, z^n_{\hat{j}}} P_{X^n Y^n_{\mathcal{J}} Z^n_{\mathcal{J}}}(x^n, y^n_{\mathcal{J}}, z^n_{\mathcal{J}}) \end{aligned}$$

for any $x^n \in \mathcal{X}^n$, $y^n_j \in \mathcal{Y}^n_j$, and $z^n_j \in \mathcal{Z}^n_j$, where the summation is over all $(y^n_{\mathcal{J}}, z^n_{\mathcal{J}}) \in \mathcal{Y}^n_{\mathcal{J}} \times \mathcal{Z}^n_{\mathcal{J}}$ such that the j-th component is (y^n_j, z^n_j).

Further, for each $j \in \mathcal{J}$, let $\tilde{\mathcal{Z}}_j$ be a finite set. Then, the formal definition of a code for our coding system is given as follows.

Definition 1: An *n-length block code*

$$C_n = (\phi_n, \psi^{(1)}_n, \ldots, \psi^{(J)}_n)$$

is defined by mappings

$$\phi_n \colon \mathcal{X}^n \to \{1, 2, \ldots, M_n\}$$

and

$$\psi^{(j)}_n \colon \{1, 2, \ldots, M_n\} \times \mathcal{Y}^n_j \to \tilde{\mathcal{Z}}^n_j, \quad \forall j \in \mathcal{J}.$$

ϕ_n is called the *encoder* and $\psi^{(j)}_n$ is called the *j-th decoder*.

The performance of a code $C_n = (\phi_n, \psi^{(1)}_n, \ldots, \psi^{(J)}_n)$ is evaluated by the coding rate and the distortion attained by C_n. The *coding rate* of C_n is defined by $(1/n) \log \|\phi_n\|$, where $\|\phi_n\|$ is the number M_n of the codewords of C_n. For each $j \in \mathcal{J}$, let

$$d^{(j)}_1 \colon \tilde{\mathcal{Z}}_j \times \mathcal{Z}_j \to [0, d^{(j)}_{\max}]$$

be a *distortion measure*, where $d^{(j)}_{\max} < \infty$. Then, for each $n \in \mathbb{N}$, the distortion between the output $\tilde{z}^n_j = (\tilde{z}_{j,1}, \ldots, \tilde{z}_{j,n}) \in \tilde{\mathcal{Z}}^n_j$ of the j-th decoder and the sequence $z^n_j = (z_{j,1}, \ldots, z_{j,n}) \in \mathcal{Z}^n_j$ to be estimated is evaluated by

$$d^{(j)}_n(\tilde{z}^n_j, z^n_j) \triangleq \frac{1}{n} \sum_{i=1}^{n} d^{(j)}_1(\tilde{z}_{j,i}, z_{j,i}).$$

Definition 2: A pair $(R, \Delta_{\mathcal{J}})$ of a rate R and a J-tuple $\Delta_{\mathcal{J}} = (\Delta_1, \ldots, \Delta_J)$ of distortions is said to be *achievable* for a source $\boldsymbol{X}$ if the following condition holds: For any $\epsilon > 0$ and sufficiently large n there exists a code $C_n = (\phi_n, \psi^{(1)}_n, \ldots, \psi^{(J)}_n)$ satisfying

$$\frac{1}{n} \log \|\phi_n\| \leq R + \epsilon$$

and, for any $j \in \mathcal{J}$,

$$\mathbb{E}_{X^n Y^n_j Z^n_j}\left[d^{(j)}_n \left(\psi^{(j)}_n(\phi_n(X^n), Y^n_j), Z^n_j \right) \right] \leq \Delta_j + \epsilon$$

where $\mathbb{E}_{X^n Y^n_j Z^n_j}$ denotes the expectation with respect to the distribution $P_{X^n Y^n_j Z^n_j}$.

Now, we state our main result. The theorem clarifies that, whenever $(R, \Delta_{\mathcal{J}})$ is achievable, $(R, \Delta_{\mathcal{J}})$ is also achievable universally.

Theorem 1: For given $(R, \Delta_{\mathcal{J}})$ and $\delta > 0$, there exists a sequence $\{\bar{C}_n\}_{n=1}^{\infty}$ of codes which is universally optimal in the following sense: For any source $\boldsymbol{X}$ for which $(R, \Delta_{\mathcal{J}})$ is achievable there exists $n_0 = n_0(\delta, \boldsymbol{X})$ such that, for any $n \geq n_0$, $\bar{C}_n = (\bar{\phi}_n, \bar{\psi}_n^{(1)}, \ldots, \bar{\psi}_n^{(J)})$ satisfies

$$\frac{1}{n} \log \|\bar{\phi}_n\| \leq R + \delta$$

and

$$\mathbb{E}_{X^n Y_j^n Z_j^n} \left[d_n^{(j)} \left(\bar{\psi}_n^{(j)}(\bar{\phi}_n(X^n), Y_j^n), Z_j^n \right) \right] \leq \Delta_j + \delta$$

for any $j \in \mathcal{J}$.

The proof of the theorem will be given in the next section.

III. PROOF OF THEOREM 1

Let $(R, \Delta_{\mathcal{J}})$ and $\delta > 0$ be given. Fix $\epsilon > 0$ satisfying

$$4J\epsilon + 2\epsilon D_{\max} \leq \delta$$

where

$$D_{\max} \triangleq \max_{j \in \mathcal{J}} d_{\max}^{(j)}.$$

For each $n \in \mathbb{N}$, let $k_n \triangleq \log \log n$.

Let $\mathcal{C}_n$ be the set of all n-length block codes $C_n = (\phi_n, \psi_n^{(1)}, \ldots, \psi_n^{(J)})$ such that $\|\phi_n\| \leq 2^{n(R+\epsilon)}$. Then, let $\mathcal{D}_n$ be the set of J-tuple $(\psi_n^{(1)}, \ldots, \psi_n^{(J)})$ of decoders such that $(\phi_n, \psi_n^{(1)}, \ldots, \psi_n^{(J)}) \in \mathcal{C}_n$ for some ϕ_n. Note that for $l \in \mathbb{N}$,

$$|\mathcal{D}_l| \leq \prod_{j \in \mathcal{J}} \left(\left| \tilde{\mathcal{Z}}_j \right|^l \right)^{(2^{l(R+\epsilon)} |\mathcal{Y}_j|^l)}. \tag{1}$$

For each $j \in \mathcal{J}$, a sequence $x^n \in \mathcal{X}^n$, and a code $C_n = (\phi_n, \psi_n^{(1)}, \ldots, \psi_n^{(J)})$, let

$$\begin{aligned} &\bar{d}_n^{(j)}(x^n, C_n) \\ &\triangleq \sum_{y_j^n, z_j^n} P_{Y_j^n Z_j^n | X^n}(y_j^n, z_j^n | x^n) d_n^{(j)} \left(\psi_n^{(j)}(\phi_n(x^n), y_j^n), z_j^n \right). \end{aligned}$$

It should be noted that, by using $\bar{d}_n^{(j)}(x^n, C_n)$, the average distortion attained by the code C_n can be written as

$$\begin{aligned} &\mathbb{E}_{X^n Y_j^n Z_j^n} \left[d_n^{(j)} \left(\psi_n^{(j)}(\phi_n(X^n), Y_j^n), Z_j^n \right) \right] \\ &= \sum_{x^n} P_{X^n}(x^n) \sum_{y_j^n, z_j^n} \Big\{ P_{Y_j^n Z_j^n | X^n}(y_j^n, z_j^n | x^n) \\ &\qquad \times d_n^{(j)} \left(\psi_n^{(j)}(\phi_n(x^n), y_j^n), z_j^n \right) \Big\} \\ &= \sum_{x^n} P_{X^n}(x^n) \bar{d}_n^{(j)}(x^n, C_n). \end{aligned} \tag{2}$$

For l ($1 \leq l \leq n$) and s ($0 \leq s < l$), let $q_{l;s}$ be the *non-overlapping empirical distribution* of x^n defined as

$$q_{l;s}(a^l | x^n) \triangleq \frac{\left| \{ 0 \leq i < \lfloor (n-s)/l \rfloor : x_{il+1+s}^{(i+1)l+s} = a^k \} \right|}{\lfloor (n-s)/l \rfloor}, \quad a^l \in \mathcal{X}^l.$$

For each $n \in \mathbb{N}$, let $\mathcal{G}_n$ be the set of all sequences $x^n \in \mathcal{X}^n$ satisfying the following condition: There are an integer l $(1 \leq l \leq k_n)$ and a code $C_l \in \mathcal{C}_l$ such that for some integer s $(0 \leq s < l)$,

$$\sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l | x^n) \bar{d}_l^{(j)}(a^l, C_l) \leq \Delta_j + 4J\epsilon, \quad \forall j \in \mathcal{J}. \tag{3}$$

Now, we describe the construction of the code $\bar{C}_n = (\bar{\phi}_n, \bar{\psi}_n^{(1)}, \ldots, \bar{\psi}_n^{(J)})$.

- *Encoder* $\bar{\phi}_n$*:* The encoder encodes a given sequence $x^n \in \mathcal{X}^n$ as follows.
  1) If $x^n \in \mathcal{G}_n$, then choose integers l, s and a code C_l satisfying (3). If $x^n \notin \mathcal{G}_n$ then error is declared[2].
  2) Send l and s by using $2 \log k_n$ bits.
  3) Send the index of decoders $(\psi_l^{(1)}, \ldots, \psi_l^{(J)}) \in \mathcal{D}_l$ by using $\log |\mathcal{D}_l|$ bits.
  4) Send the codewords $\phi_l(x_{il+1+s}^{(i+1)l+s})$ of blocks $x_{il+1+s}^{(i+1)l+s}$ $(0 \leq i < \lfloor (n-s)/l \rfloor)$ encoded by ϕ_l.
- *Decoder* $\bar{\psi}_n^{(j)}$*:* The j-the decoder decodes the received codeword as follows.
  1) Decode the first $2 \log k_n$ bits of the received codeword and obtain l and s.
  2) Decode the first $\log |\mathcal{D}_l|$ bits of the remaining part of the received codeword and obtain the decoders $(\psi_l^{(1)}, \ldots, \psi_l^{(J)}) \in \mathcal{D}_l$ chosen by the encoder.
  3) Decode the remaining part of the received codeword by using $\psi_l^{(j)}$ and the side information y_j^n. Then, the blocks $\tilde{z}_{il+1+s}^{(i+1)l+s}$ $(0 \leq i < \lfloor (n-s)/l \rfloor)$ are obtained.

  The remaining part of the output $\tilde{z}^n$, i.e. $\tilde{z}_1^s$ and $\tilde{z}_{\lfloor (n-s)/l \rfloor l+1+s}^n$, is defined arbitrarily. Note that the total length of $\tilde{z}_1^s$ and $\tilde{z}_{\lfloor (n-s)/l \rfloor l+1+s}^n$ is at most $2l$.

A. Optimality of the Code

By the fact that $1 \leq l \leq k_n$ and $\mathcal{D}_l$ satisfies (1), it is easy to see that the coding rate $(1/n) \log \|\bar{\phi}_n\|$ of $\bar{C}_n$ satisfies

$$\frac{1}{n} \log \|\bar{\phi}_n\| \leq R + \delta$$

for sufficiently large n. Hence, to show the optimality of the code $\bar{C}_n$, it is sufficient to bound the distortion attained by $\bar{C}_n$.

At first, suppose $x^n \in \mathcal{G}_n$. By (3) and the additivity of the distortion measures, the code $\bar{C}_n$ satisfies that

$$\begin{aligned}
\bar{d}_n^{(j)}(x^n, \bar{C}_n) &\leq \frac{1}{\lfloor (n-s)/l \rfloor} \sum_{i=0}^{\lfloor (n-s)/l \rfloor} \bar{d}_l^{(j)}\left(x_{il+1+s}^{(i+1)l+s}, C_l\right) + \frac{2l d_{\max}^{(j)}}{n} \\
&= \sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l | x^n) \bar{d}_l^{(j)}\left(a^l, C_l\right) + \frac{2l d_{\max}^{(j)}}{n} \\
&\leq \Delta_j + 4J\epsilon + \frac{2k_n d_{\max}^{(j)}}{n}.
\end{aligned}$$

for any $j \in \mathcal{J}$.

On the other hand, if $x^n \notin \mathcal{G}_n$ then the error is declared (and the codeword is chosen arbitrarily). In this case, the distortion occurred at the j-th decoder is upper bounded by $d_{\max}^{(j)}$.

---

[2] In this case, the encoder may choose a codeword arbitrarily and send it to the decoders. The choice of the codeword, which is sent when the error is declared, does not affect the analysis of the distortion.

Hence, for any $j \in \mathcal{J}$, we have

$$\begin{aligned}
&\sum_{x^n} P_{X^n}(x^n)\bar{d}_n^{(j)}(x^n, \bar{C}_n) \\
&= \sum_{x^n \in \mathcal{G}_n} P_{X^n}(x^n)\bar{d}_n^{(j)}(x^n, \bar{C}_n) \\
&\qquad + \sum_{x^n \notin \mathcal{G}_n} P_{X^n}(x^n)\bar{d}_n^{(j)}(x^n, \bar{C}_n) \\
&\le \sum_{x^n \in \mathcal{G}_n} P_{X^n}(x^n)\left(\Delta_j + 4J\epsilon + \frac{2k_n d_{\max}^{(j)}}{n}\right) \\
&\qquad + \sum_{x^n \notin \mathcal{G}_n} P_{X^n}(x^n) d_{\max}^{(j)} \\
&\le \Delta_j + 4J\epsilon + \frac{2k_n d_{\max}^{(j)}}{n} + P_{X^n}\left(\mathcal{G}_n^{\complement}\right) d_{\max}^{(j)} \\
&\le \Delta_j + 4J\epsilon + \frac{2k_n D_{\max}}{n} + P_{X^n}\left(\mathcal{G}_n^{\complement}\right) D_{\max} \qquad (4)
\end{aligned}$$

where $\mathcal{G}_n^{\complement}$ denotes the complement of $\mathcal{G}_n$.

Further, as shown in Lemma 1 in the appendix, if $(R, \Delta_{\mathcal{J}})$ is achievable for $\boldsymbol{X}$ then

$$P_{X^n}\left(\mathcal{G}_n^{\complement}\right) \le \epsilon \qquad (5)$$

holds for sufficiently large n.

Hence, for sufficiently large n,

$$\sum_{x^n} P_{X^n}(x^n)\bar{d}_n^{(j)}(x^n, \bar{C}_n) \le \Delta_j + 4J\epsilon + 2\epsilon D_{\max} \qquad (6)$$

By (2) and (6), the average distortion attained by $\bar{C}_n = (\bar{\phi}_n, \bar{\psi}_n^{(1)}, \ldots, \bar{\psi}_n^{(J)})$ is bounded as

$$\mathbb{E}_{X^n Y_j^n Z_j^n}\left[d_n^{(j)}\left(\bar{\psi}_n^{(j)}(\bar{\phi}_n(X^n), Y_j^n), Z_j^n\right)\right] \le \Delta_j + \delta$$

for any $j \in \mathcal{J}$. This completes the proof of Theorem 1.

APPENDIX

Lemma 1: Let $\boldsymbol{X}$ be a stationary and ergodic source for which $(R, \Delta_{\mathcal{J}})$ is achievable. Then, for sufficiently large n,

$$P_{X^n}\left(\mathcal{G}_n^{\complement}\right) \le \epsilon$$

holds.

Proof: Since $(R, \Delta_{\mathcal{J}})$ is achievable for $\boldsymbol{X}$, there are an integer l and a code C_l such that

$$(1/l)\log\|\phi_l\| \le R + \epsilon \qquad (7)$$

and

$$\mathbb{E}_{X^l Y_j^l Z_j^l}\left[d_l^{(j)}\left(\psi_l^{(j)}(\phi_l(X^l), Y_j^l), Z_j^l\right)\right] \le \Delta_j + \epsilon, \quad \forall j \in \mathcal{J}. \qquad (8)$$

For each $j \in \mathcal{J}$, let $f^{(j)}$ be a function on $\mathcal{X}^l$ such that

$$f^{(j)}(a^l) \triangleq \bar{d}_l^{(j)}(a^l, C_l) - \Delta_j - \epsilon, \quad a^l \in \mathcal{X}^l.$$

Then, (8) implies that

$$\mathbb{E}_{X^l}\left[f^{(j)}(X^l)\right] \le 0.$$

Hence, the *ergodic theorem* guarantees the following fact: There exists $n_1 = n_1(j, \epsilon, l, \boldsymbol{X})$ such that for any $n \ge n_1$ there exists a set $\mathcal{A}_n \subseteq \mathcal{X}^n$ satisfying (i) $\Pr\{X^n \in \mathcal{A}_n\} \ge 1 - \epsilon$ and (ii) for any $x^n \in \mathcal{A}_n$,

$$\sum_{a^l \in \mathcal{X}^l} p_k(a^l|x^n) f^{(j)}(a^l) \le \epsilon \tag{9}$$

where p_l is the *overlapping empirical distribution* of x^n defined as

$$p_l(a^l|x^n) \triangleq \frac{\left|\{1 \le i \le n-l+1 : x_i^{i+l-1} = a^l\}\right|}{n-k+1}, \quad a^l \in \mathcal{X}^l.$$

Note that p_l and $q_{l;s}$ satisfy that

$$(n-l+1)p_l(a^l|x^n) = \sum_{s=0}^{l-1} \lfloor (n-s)/l \rfloor q_{l;s}(a^l|x^n), \quad a^l \in \mathcal{X}^l.$$

and thus

$$\frac{(n-l+1)}{(n-l)} p_l(a^l|x^n) \ge \frac{1}{l} \sum_{s=0}^{l-1} q_{l;s}(a^l|x^n), \quad a^l \in \mathcal{X}^l. \tag{10}$$

By (9) and (10), for $n \ge n_1$ and $x^n \in \mathcal{A}_n$,

$$\frac{1}{l} \sum_{s=0}^{l-1} \sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l|x^n) f^{(j)}(a^l) \le \frac{(n-l+1)}{(n-l)}\epsilon.$$

Now, let $\mathcal{S}(j, n, x^n)$ be the set of all s such that

$$\sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l|x^n) f^{(j)}(a^l) > 2J\frac{(n-l+1)}{(n-l)}\epsilon. \tag{11}$$

Then, by the Markov lemma,

$$|\mathcal{S}(j, n, x^n)| \le \frac{l}{2J}$$

for $n \ge n_1$ and $x^n \in \mathcal{A}_n$. Further, let $\mathcal{S}(n, x^n)$ be the set of all s such that (11) holds for at least one $j \in \mathcal{J}$. Then, for $n \ge n_2 \triangleq \max_j n_1(j, \epsilon, l, \boldsymbol{X})$ and $x^n \in \mathcal{A}_n$, we have

$$|\mathcal{S}(n, x^n)| \le \frac{l}{2}.$$

Thus, for $n \ge n_2$ and $x^n \in \mathcal{A}_n$, there exists at least one s such that

$$\sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l|x^n) f^{(j)}(a^l) \le 2J\frac{(n-l+1)}{(n-l)}\epsilon, \quad \forall j \in \mathcal{J}.$$

On the other hand, we can choose n_3 such that for any $n \ge n_3$, $(n-l+1)/(n-l) \le 3/2$. Then, for any $n \ge n_4 \triangleq \max\{n_2, n_3\}$ and $x^n \in \mathcal{A}_n$, we have

$$\begin{aligned}\sum_{a^l \in \mathcal{X}^l} q_{l;s}(a^l|x^n) \bar{d}_l^{(j)}(a^l, C_l) &\le \Delta_j + \epsilon + 2J\frac{(n-l+1)}{(n-l)}\epsilon \\ &\le \Delta_j + \epsilon + 3J\epsilon \\ &\le \Delta_j + 4J\epsilon. \end{aligned} \tag{12}$$

In other words, if n is so large that $n \ge n_4$ and $l \le k_n$ then for any $x^n \in \mathcal{A}_n$ we can choose l, C_l, and s satisfying (7) and (12). This means that $\mathcal{A}_n \subseteq \mathcal{G}_n$. Hence, we have

$$P_{X^n}(\mathcal{G}_n) \ge P_{X^n}(\mathcal{A}_n) \ge 1 - \epsilon.$$

This completes the proof of the lemma. □

REFERENCES

[1] S. Kuzuoka, A. Kimura, and T. Uyematsu, “Universal source coding for multiple decoders with side information,” in *Proc. of 2010 IEEE International Symposium on Information Theory (ISIT2010),* to appear.

[2] A. D. Wyner and J. Ziv, “The rate-distortion function for source coding with side information at the decoder,” *IEEE Trans. Inf. Theory*, vol. IT-22, no. 1, pp. 1–10, Jan. 1976.

[3] C. Heegard and T. Berger, “Rate distortion when side information may be absent,” *IEEE Trans. Inf. Theory*, vol. 31, no. 6, pp. 727–734, Nov. 1985.

[4] K. J. Kerpez, “The rate-distortion function of a binary symmetric source when side information may be absent,” *IEEE Trans. Inf. Theory*, vol. 33, no. 3, pp. 448–452, May 1987.

[5] A. H. Kaspi, “Rate-distortion function when side-information may be present at the decoder,” *IEEE Trans. Inf. Theory*, vol. 40, no. 6, pp. 2031–2034, Nov. 1994.

[6] A. D. Wyner, J. K. Wolf, and F. M. J. Willems, “Communicating via a processing broadcast satellite,” *IEEE Trans. Inf. Theory*, vol. 48, no. 6, pp. 1243–1249, 2002.

[7] A. Kimura, T. Uyematsu, S. Kuzuoka, and S. Watanabe, “Universal source coding over generalized complementary delivery networks,” *IEEE Trans. Inf. Theory*, pp. 1360–1373, Mar. 2009.

[8] E. Perron, S. Diggavi, and I. Telatar, “On the role of encoder side-information in source coding for multiple decoders,” in *Proc. of 2006 IEEE International Symposium on Information Theory*, Jul. 2006, pp. 331–335.

[9] S. Jalali, S. Verdú, and T. Weissman, “A universal scheme for Wyner-Ziv coding of discrete sources,” *IEEE Trans. Inf. Theory*, vol. 56, no. 4, pp. 1737–1750, Apr. 2010.



Fig. 1. Our coding system ($J = 3$).



Fig. 2. Wyner-Ziv coding when side information may be absent.



Fig. 3. Complementary delivery.



Fig. 4. Coding system considered in [8].